

Man.: This switch can be used to manually connect the “O/I” socket to either the “I/O1” socket or to “I/O2”. In "Toggle" mode, tapping the button is enough to switch back and forth, in "Level" mode, when the button is pressed, "O/I" is connected to "I/O2", when the button is released, it is connected to "I/O1". When programming "Toggle/Level" mode or "Master/Slave" the button is used to select the operating mode for the respective switch.

Master / Slave: Button for programming the "Master" or "Slave" operating mode for each of the 8 switches. When the button is pressed, the LEDs indicate the current operating mode of the switches.

Toggle / Level: Button for programming the "Toggle" or "Level" operating mode for each of the 8 switches. When the button is pressed, the LEDs indicate the current operating mode of the switches.

